



# COMBO240

Multi-zone mixer/amplifier

Code : 9751

EAN : 3662009002699

---

## Technical data

### Front panel :

- 6-channel volume controllers and 1-channel general volume controller
- Zone selection key
- Chime activation
- Alarm activation
- 7-band equalizer
- LED view meter : -20 to + 3 dB

### Rear panel :

- 6-channel gain controllers
- Priority mode and Phantom power supply available for channel 1 and 2
- Adjustable chime and alarm volumes

### Rear inputs/outputs :

- 5-pin DIN input to control the chime
- XLR line/micro input on channels 2-5
- RCA line input on channel 6
- Remote paging via a 3-pin connector
- AMP IN and PRE-AMP OUT connections
- LINK IN et LINK OUT connections
- High-impedance loudspeakers outputs for channels 1-5
- Low-impedance loudspeakers outputs 8 to 4 Ohms

### Technical specifications:

- Dimensions : 420 x 320 x 88 mm (19 " Rack mounting brackets supplied)
- Weight : 10.8 kg
- RMS power output: 240 W RMS
- Output level / Impedance : - 100 V - 70 V - 8 and 4 Ohms