



PACK-UHF410-Hand

Set including a UHF True Diversity receiver and a handheld microphone in its transport case

Code : 10282

EAN : 3662009013534

Technical data

UHF40-BASE RECEIVER

- True Diversity receiver
- Frequency range : UHF 863 ~ 865 MHz
- 40 preset frequencies with Auto-scan function
- Channels presets : 4 groups, 4 compatible channels per group
- Channels selection : Tact Switch, Auto-Scan, SYNC
- LCD Display : frequency, group, canal, RF & AF
- XLR and Jack6.35 mono balanced and unbalanced audio output
- Line or Mic level
- Oscillator : PLL Synthesiser
- Frequency stability : $\pm 0,005\%$
- Modulation : FM
- T.H.D. :
- Audio frequency response : 80 Hz at 18kHz
- Adjust the volume with the front control knob
- Adjust the Squelch setting with the rear control knob
- BNC removable antennas, many accessories available
- Power supply : 12 V DC (adapter supplied)
- Power consumption : 260mA \pm 10mA

UHF410-HAND EMITTER

- True Diversity emitter
- Frequency ranges : UHF 863 ~ 865 MHz
- Power output : 10mW (max.)
- 40 channels with Auto-scan function
- LCD display : channel, batterie level
- Mic input via mini XLR
- Gain level: -10/0/+10 dB
- Power supply : 2x AA type 1,5V V batteries (not supplied)