



PREZONE444

Mixing desk- 8 channels 4 independent output zones

Code : 10507

EAN : 3662009015811

Technical data

- 4 symmetric Mic/Line inputs via XLR or Jack 6.35 (TRS)
- 4 stereo inputs via RCA or mono via Jack 6.35
- 4 symmetric link out outputs per zone via Phoenix plugs
- Balanced link output via Phoenix plug
- Microphone priority via input 1
- Phantom power supply for inputs 1 to 4
- Gain and tone settings (3 ways) for channels 1 to 4
- Gain settings via stereo inputs
- Tone settings (2 bands) per zone
- RJ45 Connector for WP-1 (remote input) wall controller and MIC-DESK (remote mic) for each zone
- Global Contact Mute
- Assign zones 1 to 4 to each input
- Peak and Signal display for each input
- Output display for each zone via 5-LED VU meter
- Headphones output with volume control (zones and PFL)
- Front monitoring speaker
- Screwdriver required to access technician-level settings
- Power supply: 230 V 50/60 Hz, and 24V DC
- Power consumption: 30 Watts
- Back-up power supply: 24V, DC with Link Out
- Frequency response: 20Hz – 20KHz (+/-3 dB)
- T.H.D (1 kHz nominal power):
- Equalizer:
 - High : +/-15 dB @ 12kHz
 - Mid : +/-15 dB @ 2.5 kHz
 - Low +/- 15 dB @ 80 Hz
- Dimensions: 320 x 088 x 482 mm
- 19" Rackable
- Height: 2 units
- Weight : 5 kg